


LINEAR Series



*THIS FIXTURE MUST BEEN INSTALLED WITH THIS ACCESSORIES:

Occupancy Sensor



Emergency Battery
STB41A-08WLi-55
8W 900lm 90min
(Sold separately)



FEATURES

| | |
|-----------------------|---------------|
| Voltage Range | 120 ~ 277 VAC |
| Frequency Range | 50 ~ 60 Hz |
| Power Factor | >0,95 |
| Efficiency | >140 lm/W |
| Lifetime | >100 000 h |
| Operating Temperature | -30°C ~ 45 °C |
| Installation | Surface |

DIMENSIONS



CONFIGURATION

| MODEL | POWER | OPTICS | CCT | CRI | DRIVER | ACCESSORIES | RAL COLOR |
|------------------|-------|--------------|--------------|---------|---------------------------------|---------------------------|------------|
| MFL04 Serie 1 | 22W | 120D 120° | 35K 3500K | 8 80 | 27RE 100-277 VAC. Dim 0-10V. | OS Occupancy Sensor | W White |
| | 28W | | 40K 4000K | | | IB Integral Battery | |
| | 34W | | 50K 5000K | | | N/A No Accessories | |
| | 40W | | | | | | |

REFERENCES

| References | 4000K | |
|-----------------------------|--------|--------|
| | Lumens | lm / w |
| MFL04-34W-120D-40K8-27RE-WH | > 4964 | >146 |
| MFL04-40W-120D-40K8-27RE-WH | > 5720 | >143 |